


# Support for various SSIDs per AP Profile

## Background

- Several SSIDs are normally defined for each AP profile.
- An SSID is then in turn linked to an exit point.
- These defined SSIDs are applied to all APs belonging to an AP profile.
- One of our customers requires an option to define individual SSIDs/passwords for individual APs and at the same time have a single SSID that also applies to all APs.
- To meet our customer's requirements, we have made the following improvements.

## Apply to all or selected APs

- When defining an SSID, you can set a flag to specify whether it should be applied to all APs.



## Apply static SSID to AP

- When adding or editing an AP to the AP profile, you can now select from the pool of static access points (access points for which the Apply to all option is not activated)
- Once you have selected an item from the list, there is additional options to override certain values.
- These are:
  - **SSID**
  - **Pre-Shared Key** if WEP or WPA personal security is set for the SSID.
  - **VLAN number** if the selected SSID is connected to a VLAN exit point.

The screenshot shows the RADIUSdesk NETWORK interface. At the top, there is a navigation bar with tabs for Meshes, Mesh Nodes, AP Profiles, APs, New Arrivals - Hardware, Jhb-South, and Adv-Test. The main content area is for configuring an AP profile named 'Adv-Test'. The configuration includes:

- Grouping:** Jhb-South (with a 'Change Gro...' button), Site Jhb-South, and Network Jhb-South.
- Profile:** Jhb-South (dropdown menu).
- Name:** Adv-Test (text input).
- Description:** (empty text input).
- Hardware Model:** Xiaomi 4C 300M (dropdown menu).
- MAC Address:** 9C-9D-7E-83-4B-93 (text input).
- Static entry points:** Jhb-South Wireless x (dropdown menu).
- Override:** A green highlighted section with a checked checkbox for 'Override: Jhb-South Wireless'.
- SSID:** RADIUSdesk 2023 (text input).
- Key:** 88888888 (text input).
- Internet Connect:** Auto Detect (dropdown menu).
- Admin VLAN:** (empty text input).
- Reboot When Controller Can't Be Reached:** (unchecked checkbox).


## Visual indication

- To make things easy to recognize, we add a small visual hint in the AP list to show that the SSID value has been overwritten.

Meshes Mesh Nodes AP Profiles APs New Arrivals - Hardware Jhb

Refresh Add Delete Edit Search Settings Power Export

Profile	Name	MAC Address
Jhb-South	Adv-Test	9C-9D-7E



### Adv-Test

Xiaomi 4C 300M

#### DEVICE INFORMATION (for the past hour)

- Online (last check-in 18 seconds ago ago).
- Jhb-South Guest had 0 users.
- RADIUSdesk 2023 had 0 users.
- Public IP 41.117.219.72.
- Data usage 203.76M.
- Last connection from 68:17:29:D2:AC:62 which was 6 minutes ago ().
- LAN IP: 192.168.8.130 LAN Gateway: 192.168.8.1 (dhcp)

From: <http://www.radiusdesk.com/wiki/> - **RADIUSdesk**

Permanent link: <http://www.radiusdesk.com/wiki/apdesk/multiple-ssids>

Last update: **2023/11/26 16:56**

